

FD310

Beam rookdetector, zender-ontvanger 5 tot 120 m

General

The FD310 End to End infrared Optical Beam Smoke Detector (OBSD) has been designed using the latest optical technology, incorporating modern industrial, electronic and software techniques. This detector offers cost effective protection of large, open area spaces with high ceilings. It is also very suited to applications where access to ceiling mounted smoke detectors presents practical difficulties.

Operation

The system comprises a modern looking Transmitter head, which emits a narrow beam of infra-red light to an associated Receiver head, with a compact Low Level Controller. Once smoke crosses through and thus obscures the IR beam path, the signal strength at the Receiver drops below a preset level which in turn results in an alarm condition. Both the detector heads, Transmitter and Receiver, have integrated alignment thumbwheels for ease of alignment. Using these thumbwheels provides a smooth and repeatable alignment process. The detector heads have up to 10 degrees of adjustment in both planes. For further adjustment, a bespoke Adjustment Bracket is available, which offers up to 180 degrees movement in both planes, as well as a full 360-degree rotation.

The FD310 has been designed so that it can be installed by one operator, with its laser assisted alignment method combined with easy to use alignment LED's offering a visual feedback. Integrated laser alignment aid can be activated at the Controller or at the Receiver head.

The low level Controller incorporates a LCD display, which offers a full icon-based, easy-to-use interface unit. This Controller enables ease of commissioning, testing and maintenance of the beam detection system. During commissioning the detector sensitivity and fire thresholds can be selected, along with the user variable time to fire and time to fault settings.



Details

- Separate Transmitter and Receiver Heads
- Range 5 to 120 metres, configurable per set of Detectors
- Integral Laser Alignment in Receiver
- 2-wire Interface between Controller and Receiver
- Single and Twin Detector options
- Separate Fire and Fault Relays per Detector
- Low Level Controller with LCD display
- Programmable Sensitivity and Fire Threshold
- Automatic Gain Control (AGC) for drift compensation
- First Fix concept for Transmitter, Receiver and Controller
- Multiple cable gland knockouts for ease of wiring
- Optional Transmitter powering from Controller

FD310

Beam rookdetector, zender-ontvanger 5 tot 120 m

Technische specificaties

Elektrisch

Bedrijfsspanning	12 to 36 VDC
Stroomverbruik	14 mA (controller) 8 mA (transmission head)

Detectie

Bereik	5 to 120 m
--------	------------

Uitgang

Type uitgang en classificatie	Relay output 2A @ 30 VDC
-------------------------------	--------------------------

Fysiek

Fysieke afmetingen	Controller: 203 x 124 x 73 mm (W x H x D) Head: 74 x 74 x 161 mm (W x H x D)
Netto gewicht	606 g (controller) 104 g (transmission head)
Kleur	Wit
Type montage	Muurmontage

Omgeving

Bedrijfstemperatuur	-10 to +55°C
Omgeving	Binnen
IP-classificatie	IP54 (controller and head)

Regelgeving

Certificering	EN54-12
---------------	---------

Compatibele producten

Categorie	Referentie	Beschrijving
Detectieapparatuur	FD-MB50	Montage steun voor montage FD310 set
Detectieapparatuur	FD310H	Additionele zend-ontvanger set voor FD310



Als een bedrijf van innovatie behoudt Kidde Global Solutions zich het recht voor productspecificaties zonder kennisgeving te wijzigen. Ga voor de nieuwste productspecificaties online naar nl.firesecurityproducts.com of neem contact op met uw verkoopvertegenwoordiger.

Last updated on 4 June 2025 - 14:58