2X-AT-F2-FB-S

Addressable fire panel w touchscreen and fire brigade controls, 2 loop, small cabinet

Overview

The new 2X-A series life safety control systems bring the speed and functionality of high-end intelligent processing to small to mid-sized addressable applications. Based on 2X series learned experience and with complete backwards compatibility, the new 2X-A features an attractive contemporary design that fits with any decor. With improved robustness, manufactured in metal, special plastics and easy electronics removal, it allows painting in any colour. The main controls are easily located using an improved and robust jog dial.

With high power loop addressable detection, a full line of easily configured option cards and modules, as well as USB and Ethernet® connectivity, these quick-to configure systems offer versatility that benefits building owners and life safety system installers alike.

This version of 2X-A panels includes a 7 inches touchscreen improving the user experience thanks to the more intuitive user interface.

The Panel


The fire panels supplied in local language, with user interface with fire brigade and fire protection controls, with 2 loops that supports up to 256 devices in 512 zones, have standard 4 supervised sounder/fire-routing outputs, which can be used as freely programmable outputs as well. In addition 2 conventional relay outputs and 2 supervised outputs, working in pair and dedicated to common fire and fault conditions, as well as 2 user configurable inputs for monitoring and control are available.

Options

The panel supports one network board to create a maximum of 64 nodes / 256 loops network of fire panels and fire panel repeaters (including conventional fire panels and fire repeater panels up to a maximum of 64 conventional zones). Last but not least, in case seperate zone indications are required, a 20 or a 40 zone fire/fault LED indicator board can be mounted in the panel or repeater with ample space for custom text.

High loop power PAK available to increase the loop power from 500 mA to 800 mA.

Compatible with existing loop devices and network compatible with existing panels, repeaters (existing and new) and conventional panels.



Détails

- 2 High Power Loops with 500 mA per loop and Fire Brigade & Fire Protection controls
- 7" touchscreen
- High loop power PAK to increase the loop power from 500 mA to 800 mA
- Up to 256 devices, 512 zones and 300 output groups
- Up to 24 LED Zone indicators for Fire and Fault with space for a 4 digit number
- Auto configuration, setup wizards and default regional setup modes
- Ethernet port with TCP/IP for remote diagnostics, maintenance and programming
- EN54 compliant graphical LCD with icons and up to 256 zones
- Improved Jog Dial with 4 soft buttons for simple and intuitive user control
- Aesthetic pleasing design with robust painted steel door
- Easy removable door and chassis for quick and clean installation
- All pluggable connectors
- Auxiliary 24 VDC supply output with reset support
- 3 USB ports with memory stick support and RS232 for printer support
- Communication via UltraSync cloud, using EN 54-21 UC240 UltraSync communicator
- Integration in management software ATS8600, allowing integration with security systems and CMS
- 3 operator level menu structure (20 usernames and passwords)
- Email notification for events directly from the panel (4 user accounts)
- History log memory for 9999 events

2X-AT-F2-FB-S

Addressable fire panel w touchscreen and fire brigade controls, 2 loop, small cabinet

Spécifications techniques

Général

Interface utilisateur	Avec contrôle des pompiers
Capacité maximale du système (comptage de périphérique)	up to 32512
Taille du réseau (nœuds)	Jusqu'à 64

Électrique

Type de bloc d’alimentation	VAC
Tension de fonctionnement	110 / 240 VAC (+10%/-15%) Cable type: 3 x 1.5 mm² (live, neutral, earth)
Consommation de courant	Nom. 0.6 / 1.3 A, Max. 1.5 A / 3.15 A

Boucle

Capacité maximale de boucle de masse	2
Type et classe	500 mA expandable to 800 mA at 37 VDC (28 to 37 VDC)
Cote de câble	52 ohm, 500 nF, max. 2 km, Cable type: Recommended 2 core 1.5 mm² twisted pair

Zone

Capacité maximale de zone	Jusqu'à 512

Entrée

Quantité entrée	2
Type d'entrée et classe	Supervised, maximum load 150 mA
Programmable	2
Résiliation	15 kohm

Sortie

Alarme incendie signalisation	350 mA / 21 to 28 VDC (24 VDC nominal)
Signalisation de défaut	350 mA / 21 to 28 VDC (24 VDC nominal)
Notification	8 sounder outputs
Surveillance tension	Supervised, 4, 750 mA / 21 to 28 VDC (24 VDC nominal)
Alimentation auxiliaire	1 resetable, 500 mA / 21 to 28 VDC (24 VDC nominal)
Programmable	Up to 8 (2 per loop board) / 21 to 28 VDC (24 VDC nominal)
Résiliation	15 kohm

Batterie de secours

Capacité	Max. 2 x 12 V / 18 Ah
En charge	27.3 V at 20ºC ; 36 mV/ºC
Seuil d'avertissement de batterie faible	23.6 VDC ± 1% at 25ºC
Batteries supportées dans le boîtier	Max. 2 x 12 V / 7.2 Ah

Caractéristiques physiques

Types de format	Petit
Dimensions physiques	409 x 285 x 154 mm (W x H x D)
Poids net	5.2 kg (without battery)
Poids à l'expédition	6.6 kg
Couleur	Blanc (RAL 9003)
Type de montage	Montage en surface
Entrées de câble	18 (20 mm) / 2 (20 mm) / 2 removable plates (top / bottom / back)
Matériel	Acier (peint)

Environnement

Température de fonctionnement	-5 to +40°C
Température de stockage	-20 to +50°C
Humidité relative	10 to 95% noncondensing
Environnement	Intérieur
Indice de protection	IP30, indoor use only

Régulateur

Conformité	CE, REACH, RoHS 3, WEEE
Certification	AEAI, BOSEC, CPR
Normes	EN54-2, EN54-4, EN54-13, EN54-21

Output

General Fire + Fault supervised	2, 350 mA, 19.5 to 28 VDC (24 VDC nominal)

Loop

Outputs	250 mA, 29 VDC (29 to 36 VDC)

Regulatory

Additional Approval	DBI

KIDDE COMMERCIAL

En tant que société d'innovation, Kidde Global Solutions se réserve le droit de modifier les spécifications des produits sans préavis. Pour les dernières spécifications du produit, visitez le site web be.firesecurityproducts.com ou contactez votre représentant commercial.

Last updated on 9 September 2026 - 9:40