

PT971

Interfaccia ad 1 canale.

General

The PT971 is a single channel protocol translator for the 970 series analogue addressable intrinsic safe sensors. It must be used with the GBX70 barrier.


Application

To enable the use of standard control (NON IS) fire panels in intrinsically safe systems, a device to “translate” voltage levels from the loop to levels compatible with the I.S. requirements is required. The PT971 also “boosts” the current pulses returned by the I.S. detectors.

The PT971 is a loop-powered device that draws a low quiescent current and is therefore transparent to both the loop driver and the I.S. detectors.

Construction

The translator is housed in a moulded plastic enclosure that can be either clipped onto a standard 35mm DIN rail (DIN 46277) or panel mounted by using pull-out latches in the base. The PT971 should only be connected to a single intrinsically safe circuit through an appropriate safety barrier. Each channel is thus capable of supplying up to twenty 970 series I.S. devices.



Dettagli

- 900 Series protocol compatible
- Connects 1 IS zone to a standard fire panel
- DIN or panel mount options
- No configuration required
- Interfaces with the GBX70 IS barrier

PT971

Interfaccia ad 1 canale.

Specifiche tecniche

Elektrico

Operating voltage	19 to 28 V
-------------------	------------

Fisico

Dimensioni fisiche	92.5 x 110 x 20 mm
--------------------	--------------------

Peso netto	± 100 g
------------	---------

Tipo di montaggio	barra DIN
-------------------	-----------

Materiale (scatola)	Makrolon 6485 - UL94V-0
---------------------	-------------------------

Ambientale

Temperatura operativa	-20 to +60°C
-----------------------	--------------

Relative humidity	10 to 95% noncondensing
-------------------	-------------------------

Ambiente	Interno, IS
----------	-------------

Regolatorio

Certificazioni	CENELEC/ATEX
----------------	--------------

Electrical

Modulation voltage at translator	5 to 9 V (peak-to-peak)
----------------------------------	-------------------------

Input current (no load)	1 mA max.
-------------------------	-----------

Input pulse current (from 8 to 12 mA barrier)	
---	--

Output voltage (to barrier)	16.5 to 19 V
-----------------------------	--------------

Output current (to barrier)	0.2 to 30 mA
-----------------------------	--------------

Output pulse current (from loop)	17 to 23 mA
----------------------------------	-------------



In quanto azienda in continua innovazione, Kidde Global Solutions si riserva il diritto di modificare le specifiche del prodotto senza preavviso. Per avere informazioni sempre aggiornate, visita it.firesecurityproducts.com online o contatta il tuo riferimento commerciale.

Last updated on 14 May 2024 - 15:23