

2X-F1-FB2-S-46

Addressable Fire Panel with Fire Brigade controls - 1 Loop small cabinet

Overview

The 2X Series life safety control systems are bringing the speed and functionality of high-end intelligent processing to small to mid-sized addressable applications. They feature an attractive contemporary design that fits with any decor. Special plastics allows for painting in any color and the easy to remove electronics will support in this matter. The gently lined door with the intuitive dark inset user interface and EN54 compliant graphical LCD offers a distinctive flair. The main controls are clearly, but discreetly highlighted with the focus on the central located Jog Dial.

With the addressable detection and a full line of easily configured option cards and modules, USB and Ethernet® connectivity, these quick-to-configure systems offer versatility that benefits building owners and life safety system installers alike.

The Panel

The fire panels supplied in local language, with user interface with fire brigade and fire protection controls, with 1 loop that supports up to 128 devices in 512 zones, have standard 2 supervised sounder/fire-routing outputs, which can be used as freely programmable outputs as well. In addition 2 conventional relay outputs and 2 supervised outputs, working in pair and dedicated to common fire and fault conditions, as well as 2 user configurable inputs for monitoring and control are available.

Options

The panels supports one network board to create a maximum of 32 nodes / 32 loops network of fire panels and fire panel repeaters (including conventional fire panels and fire panel repeaters up to a maximum of 64 conventional zones). Last but not least, in case separate zone indications are required, a 24 zone fire/fault LED indicator board can be mounted in the panel or repeater with space for a 4 digit number.

Approvals & Compliance

- CE / CPD / EN54-2 / EN54-4 / EN54-21
- NEN2535 / NBNS21-100 compliant
- BS5839-1 compliant
- VdS and LPCB certified
- WEEE / RoHS compliant



Szczegóły

- 1 loop with up to 512 zones with Fire Brigade & Fire Protection controls and 300 output groups
- Up to 24 LED Zone indicators for Fire and Fault with space for a 4 digit number
- Auto configuration, setup wizards and default EN54 setup modes
- Ethernet port with TCP/IP for remote diagnostics, maintenance and programming
- EN54 compliant graphical LCD with icons and up to 256 zones
- Jog Dial with 4 soft buttons for simple and intuitive user control
- Aesthetic pleasing design with special paintable synthetic door
- Easy removable door and chassis for quick and clean installation
- All pluggable connectors
- 3 USB ports with memory stick support and RS232 for printer support
- Email notification for events directly from the panel (4 user accounts)
- Auxiliary 24VDC supply output with reset support
- 3 operator level menu structure (20 usernames and passwords)
- History log memory for 9999 events
- Up to 24 hours standby time and 30 minutes alarm
- Compatible with the new loop powered sounders/beacons and base sounders and the 2000 series detectors with replaceable optical chamber

2X-F1-FB2-S-46

Addressable Fire Panel with Fire Brigade controls - 1 Loop small cabinet

Specyfikacja techniczna

Ogólne

Maximum system capacity (device count)	do 8192
Wielkość sieci (liczba węzłów)	do 64

Elektryczne

Typ zasilacza	VAC
Napięcie znamionowe	110/230 VAC (+10%/-15%) 50 / 60 Hz (±5%)
Current consumption	Nom. 0.6 / 1.3 A, Max. 1.5 / 3.15 A 2 / 4 A (fuse rating)

Pętla

Dopuszczalna pojemność pętli	
Typ i obciążalność	Recommended 2 core 1.5 mm ² twisted pair (cable)
Klasa kabla	52ohm / 500nF max. 2km (length)

Strefa

Maksymalna liczba stref	do 512
-------------------------	--------

Wejście

Typ i obciążalność wejścia	150 mA (maximum load); Recommended 2 core 1.5 mm ² twisted pair (cable)
Programowalny	2
Terminacja	15 kohm (EOL resistor)

Wyjście

Typ i obciążalność wyjścia	Recommended 2 core 1.5 mm ² twisted pair (cable)
Sygnalizacja pożaru	2 x General Fire + Fault relay
Zasilacz dodatkowy	1 resetable, 500mA / 19.5-28VDC (24VDC nominal)
Programowalny	2, 750mA / 19.5-28VDC (24VDC nominal) (supervised)
Terminacja	15 kohm (EOL resistor)

Bateria rezerwowa

Pojemność	Max. 2 x 12V/7.2Ah (use supplied cables)
-----------	--

Fizyczne

Forma	Mały
Wymiary	410 x 298 x 162 mm (W x H x D)
Masa netto	5.2 kg (without battery)
Masa brutto	10.1 kg
Kolor	Szary (RAL 7035)
Typ montażu	Montaż nawierzchniowy
Cable entries	9 (20mm) / 2 (20mm) / 2 removable plates (Top / Bottom / Back)

Środowiskowe

Operating temperature	-5 to +40°C
Temperatura magazynowania	-10 to +50°C
Wilgotność względna	95% max. noncondensing
Środowisko	Wewnętrzne
Szczelność IP	IP30: for indoor use only

Regulacyjnych

Zgodność	BS5839-1, CPD, LPCB, NBNS21-100, NEN2535, RoHS, WEEE
Certyfikacja	EN54-13, EN54-2, EN54-21, EN54-4, VdS

Electrical


Mains supply cable type	3 x 1.5 mm ² (live, neutral, earth)
-------------------------	--

Output

General Fire + Fault supervised	2, 350mA / 19.5-28VDC (24 VDC nominal)
---------------------------------	--

Loop

Outputs	250 mA / 29VDC (29VDC to 36VDC)
---------	----------------------------------



Będąc firmą innowacyjną, Carrier Fire & Security zastrzega sobie prawo do zmian w specyfikacji wyrobów bez uprzedzenia. W celu uzyskania najnowszych specyfikacji prosimy o wizytę na stronach [pl/firesecurityproducts.com](http://firesecurityproducts.com) lub kontakt z przedstawicielem handlowym.

Last updated on 16 February 2024 - 12:24