2X-FR-FB2-S-11

Addressable Fire Panel Repeater with Fire Brigade controls - Small cabinet - Dutch Belgian

Overview

The 2X Series life safety control systems are bringing the speed and functionality of high-end intelligent processing to small to mid-sized addressable applications. They feature an attractive contemporary design that fits with any decor. Special plastics allows for painting in any color and the easy to remove electronics will support in this matter. The gently lined door with the intuitive dark inset user interface and EN54 compliant graphical LCD offers a distinctive flair. The main controls are clearly, but discreetly highlighted with the focus on the central located Jog Dial.

With the addressable detection and a full line of easily configured option cards and modules, USB and Ethernet® connectivity, these quick-to-configure systems offer versatility that benefits building owners and life safety system installers alike.

The Panel

The fire panel repeaters, with user interface with fire brigade and fire protection controls, supplied in local language come with a 2010-2-NB network board already fitted. Except for having no addressable loops and corresponding programmable outputs, the setup is similar as a normal fire panel. It and has its own power supply, 2 conventional relay outputs and 2 supervised outputs, working in pair and dedicated to common fire and fault conditions, as well as 2 user configurable inputs for monitoring and control are available.

Options

The repeaters use a node on the network, similar like a normal panel with a maximum of 32 nodes / 32 loops network of fire panels and fire panel repeaters (including conventional fire panels and fire panel repeaters up to a maximum of 64 conventional zones). Last but not least, in case seperate zone indications are required, a 24 zone fire/fault LED indicator board can be mounted in the panel or repeater with space for a 4 digit number.

Approvals & Compliance

- CE / CPD / EN54-2 / EN54-4 / EN54-21
- NEN2535 / NBNS21-100 compliant
- BS5839-1 compliant
- VdS and LPCB certified
- WEEE / RoHS compliant

Detaljer

- Local or global repeater with Fire Brigade and Fire Protection controls with or without global control functionality
- Up to 24 LED Zone indicators for Fire and Fault with space for a 4 digit number
- Auto configuration, setup wizards and default EN54 setup modes
- Ethernet port with TCP/IP for remote diagnostics, maintenance and programming
- EN54 compliant graphical LCD with icons and up to 256 zones
- Jog Dail with 4 soft buttons for simple and intuitive user control
- Aesthetic pleasing design with special paintable synthetic door
- Easy removable door and chassis for quick and clean installation
- All pluggable connectors
- 3 USB ports with memory stick support and RS232 for printer support
- Email notification for events directly from the panel (4 user accounts)
- Auxiliary 24VDC supply output with reset support
- 3 operator level menu structure (20 usernames and passwords)
- History log memory for 9999 events
- Up to 24 hours standby time and 30 minutes alarm
- Comes standard fitted with network board

2X-FR-FB2-S-11

Addressable Fire Panel Repeater with Fire Brigade controls - Small cabinet - Dutch Belgian

Tekniske specifikationer

Generelt

Netværksstørrelse (noder)	up to 64

Elektrisk

Strømforsyningstype	VAC
Driftsspænding	110/230 VAC (+10%/-15%), 50 / 60 Hz (±5%) Cable type: 3 x 1.5 mm² (live, neutral, earth)
Nuværende forbrug	Nom. 0.6 / 1.3 A, Max. 1.5 / 3.15 A 2 / 4 A (Fuse rating)

Input

Indgangstype og klassificering	150 mA (max. Load), Cable Type: Recommended 2 core 1.5 mm² twisted pair
Programmerbar	2
Afslutning	15 kohm

Udgang

Output type og klassificering	Cable type: Recommended 2 core 1.5 mm² twisted pair

Standby batteri

Kapacitet	Max. 2 x 12 V, 7.2 Ah (use supplied cables)

Fysisk

Form faktor	Lille
Fysiske dimensioner	410 x 162 x 298 mm (W x H x D)
Nettovægt	5.2 kg (without battery)
Forsendelsesvægt	6.6 kg
Farve	Grå (RAL 7035)
Monteringstype	Overflademontering
Kabelindgange	9 (20 mm) / 2 (20 mm) / 2 removable plates (Top / Bottom / Back)

Miljø

Driftstemperatur	-5 to +40°C
Stuetemperatur	-10 to +50°C
Relativ luftfugtighed	95% max. noncondensing
Miljø	Indendør
IP-vurdering	IP30: for indoor use only

Regulerende

Overholdelse	BS5839-1, CPD, LPCB, NBNS21-100, NEN2535, RoHS, WEEE
Certificatie	EN54-2, EN54-21, EN54-4, VdS

Output

General Fire + Fault supervised	2, 350 mA, 19.5 to 28 VDC (24 VDC nominal)
General Fire + Fault relay	2
Aux	1 resetable, 500 mA, 19.5 to 28 VDC (24 VDC nominal)



Carrier Fire & Security er et innovativt selskab og forbeholder sig ret til at ændre produktspecifikationer uden varsel. De nyeste produktspecifikationer kan du finde på dk.firesecurityproducts.com eller ved at kontakte din salgsrepræsentant hos.

Last updated on 23 July 2024 - 9:15