TX-5011-03-3

Shock sensor 868 MHz Gen2, brown

Product overview

The shock sensor is designed to detect the vibrations made by an intruder trying to break a window or door. The sensor has an internal reed allowing to supervise a door or window using the door magnet that is included.

Sensitivity and pulse count options can be set using DIP switches. A jumper allows to select which reed is in use (left or right or none). In walk-test mode, the blue LED on the front cover will light up when the sensor is in alarm state.



Details

- Learn-Mode technology
- Supervised transmissions
- LED indicating sensor status
- Detects opening of door or window
- Magnet included
- Gross attack and pulse count detection modes
- Compatible with Interlogix 868 MHz Gen2 receivers

TX-5011-03-3

Shock sensor 868 MHz Gen2, brown

Technical specifications

General

Product type	Magnetic contact, Shock with analyser

Wired / wireless

Wired / wireless	Wireless
Wireless frequency	868 MHz AM

Electrical

Current consumption	10 µA (typical standby)
Batteries	1 x 3 V Lithium
Battery lifetime	3 to 5 years

Physical

Physical dimensions	114 x 32 x 32 mm
Colour	Brown

As a company of innovation, Kidde Global Solutions reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.

Last updated on 18 June 2026 - 14:33