

SC-43-0200-0001-99

SmartCell Contact Transmitter and Input Device for Information Zones

Overview

The SmartCell Input Device is quick and easy to install and offers individual addressing at the SmartCell Control Panel. The device allows non fire to be monitored at the SmartCell Control Panel and to an information alert when activated. Examples may include the monitoring of doors (opening/closing), a loss of power to your fridge, flood detection and an alarm condition on your intruder system.

Features include a resistor monitored input, an alternative magnetic contact option and bidirectional 868 MHz communication.

This device is third party certified and compatible with the full SmartCell product range.



Details

- Full wireless communication with panel
- Quick and easy to install
- Resistor monitored input
- Alternative magnetic contact option (magnet supplied)
- For connection to remote information devices
- NOT FOR FIRE APPLICATIONS

SC-43-0200-0001-99 SmartCell Contact Transmitter and Input Device for Information Zones

Technical specifications

868 MHz
1
Resistor monitored input
30 x 110 x 28 mm (W x H x D)
0.05 kg
White
Wall mount
1 x ER14505M 3.6 V lithium thionyl chloride battery (Fanso or Titus)
-10 to +55°C
-10 to +30°C (with battery) -10 to +55°C (without battery)
95% noncondensing max.
Indoor
CE
R&TTE



As a company of innovation, Kidde Global Solutions reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.