ATS1115A-N

Advisor Advanced keypad 2x16 characters LCD with integrated card reader

Remote arming stations

The ATS1115A is part of the Advisor Advanced product family. A range of keypads and card readers is available that can be used in different environments, in and out-door. The ATS1115A can be used for configuration and management of the system, as well as for opening doors and arming/disarming areas. In an easy way, the ATS1115A gives a status overview from your security system with both visual and audio indicators.

Product overview

The ATS1115A is a modern ergonomic design and has a clearly readable text on a 2 x 16 characters LCD for displaying system programming, alarm and access control functions. The viewing angle of the display is adjustable via the keypad as well as the volume level of the built-in buzzer. Four arrow keys will navigate the user easily through the programming and operational features and 4 additional functions key will complete this user-friendly interface.

Built-in card reader

The ATS1115A has a built in smart card reader. The ATS1115A can be used for arming/disarming using either the PIN or the card or a combination of the two for higher security needs. It is suitable for using the multiple card badging techniques which are available for the Advisor Advanced product family. A user can set the system in the evenings by badging his card three times within 10 seconds interval. Another application could be for doors which can be programmed so that badging once unlocks the door to allow people in and out without card, and badging three times re-locks the door.

Indications

Four status LED's will continuously update the user on mains condition, faults, access control and alarms.
Green (Power), Yellow (Fault), Blue (Access) and Red (Alarm) are controlled by the control panel.
The Arming Station can display the status of 16 areas using 16 LED's on the front, while the LCD shows details of alarms or a pre-programmed text.
The area may be identified by viewing the 16 area LEDs visible when the RAS cover is open or removed and the indicates area is armed (on), area in fault (slow flash) and area alarm (fast flash)

Mounting

The RAS cover is hinged at the bottom. To open, grasp the cover at the sides or the top and pull gently — the cover will swing down on its pins. The cover may be fully removed by gently prising one of the pins away from the body of the RAS and pulling. The metal mounting plate at the rear is held by a locking screw.



Détails

- 2 x 16 characters LCD
- User adjustable buzzer
- User adjustable LCD contrast
- Compatible with Axon and Advisor Advanced panels
- 16 Area indication
- Door release indication
- Built-in smart card proximity reader

ATS1115A-N

Advisor Advanced keypad 2x16 characters LCD with integrated card reader

Spécifications techniques

Général

Interface utilisateur	2 x 16 Caract. LCD, Touch Buttons
Gamme de produits	Advisor Advanced
LED d'état	16
Lecteur intégré	Proximité

Système

Touches de fonction	4
Types de cartes pris en charge	HiTag2
Type d'adressage	DIP Switches
Type de câble pris en charge	WCAT 52/54 or equivalent

Communication

Type de communication	Câblés
Distance de lecture	6 to 10 cm

Entrées / sorties

Entrées	1
Type d'entrée	Request to Exit
Sorties	1
Type de sortie	Open collector, 50 mA Max

Électrique

Tension de fonctionnement	9 to 14 VDC
Consommation de courant	35 mA typical 165 mA max.

Caractéristiques physiques

Dimensions physiques	92 x 165 x 25.4 mm
Couleur	Blanc
Types de format	Vertical
Couvercle	Flip Cover
Type de montage	Montage en surface

Environnement

Température de fonctionnement	0 to +50°C
Humidité relative	0 to 95% noncondensing
Environnement	Intérieur
Indice de protection	IP30

Régulateur

EN50131 Grade	Grade 3
Conformité	CE, RoHS
Certification	VdS

En tant que société d'innovation, Kidde Global Solutions se réserve le droit de modifier les spécifications des produits sans préavis. Pour les dernières spécifications du produit, visitez le site web be.firesecurityproducts.com ou contactez votre représentant commercial.

Last updated on 16 June 2026 - 15:21