FBF2001

Fire-Brigade Control Panel in accordance with DIN14661

General

The FBF2001 is a DIN14661 standard fire brigade interface and is an additional device for connection to a fire alarm control panel. It allows for the visualization of certain operating conditions of the fire alarm panel in a uniform way that makes it possible for fire brigade personnel to view and control emergency events on the fire panel without assistance of the fore panel operator.

Easy Installation

The connection to the FBF2001 is made by an 11-core cable from the VDS2000 board installed on the FP1200/2000 series addressable fire panels. One easy programming step on the fire panel makes the full functionality of the FBF2001 possible.



Détails

- Direct connection to a VDS2000 board
- Conformance with DIN14661
- Front layout with door lock for half profile cylinders according to DIN18252
- LED control - active high or active low
- Button high or low switching
- Acoustics off with switch function
- "BFS off" with relay change over switch
- VdS approved

FBF2001

Fire-Brigade Control Panel in accordance with DIN14661

Spécifications techniques

Électrique

Tension de fonctionnement	12 to 24 VDC
Consommation de courant	±75 mA (Alarm) ±18 mA (Quiescent)

Caractéristiques physiques

Dimensions physiques	255 x 185 x 58mm (W x H x D)
Poids net	3.4 kg
Poids à l'expédition	2.611 kg
Couleur	Gris (RAL 7032)
Type de montage	Montage en surface
Matériel	Tôles d’acier

Environnement

Température de fonctionnement	0 to +50°C
Environnement	Intérieur
Indice de protection	IP30

En tant que société d'innovation, Kidde Global Solutions se réserve le droit de modifier les spécifications des produits sans préavis. Pour les dernières spécifications du produit, visitez le site web be.firesecurityproducts.com ou contactez votre représentant commercial.

Last updated on 13 May 2024 - 17:03