

FP1216C-18

1200 Series - Addressable Fire Panel with 2-4 Loops 16 Zone LED's - Polish

General

The FP1216C is a versatile addressable fire panel supplied with 2 class-A loops. In addition to a generous backlit LCD display, it provides LEDs for indicating both fire and fault conditions with text descriptions for 16 fire zones on the front panel user interface. The panel may be upgraded with an additional 2 class-A loops, full inter-panel networking facilities on both copper or fibre, as well as with a LON network bus that supports the Aritech LON700 devices and repeaters, amongst others.

The FP1216C provides extensive maintenance features, boasts powerful I/O programming and supports both Aritech 2000 and 900 series protocols.

Installer Friendly

The FP1216C offers multiple auto-configuration options with extensive auto detection facilities facilitating quick initial setup even for large systems. Multiple repeaters in various formats may be connected over a 2-wire network with both class-A and B operating modes, whilst up to 31 fire panels may be networked together for large applications.

User friendly

In addition to the comprehensive information LEDs, the panel's large LCD display allows for every device in the system to be described with up to 80 characters of descriptive text, as well as 40 characters for zone descriptions. Complete statistics and graphics indications for every device are available.

Several mechanisms for preventing false alarms, including floating background with automatic compensation, double knock and coincidence mode within and between zones, as well as soak test facilities allow the user complete piece of mind.

Maintenance friendly

Maintenance warnings are available whenever detectors reach contamination levels. Together with real time diagnostics and statistics per sensor, the FP1216C offers a wealth of in-depth information locally or by remote connections.

LON700 Modules

Up to 32 LON700 nodes are supported on the optional LON700 network. This includes LCD and LED repeaters, synoptic chart drivers, supervised in- and output boards, relay and open collector output boards, zone monitors and power supplies.



Détails

- Configuration, maintenance and graphic PC software support
- Up to 128 device addresses per loop
- Full interpanel network options
- Full range of repeaters and LON700 devices including Dutch and Scandinavian fire brigade panels, and Scandinavian alarm delay units
- Networkable "black box" panels
- Power supply for 72-hour autonomy
- Default start-up and service modes
- Programmable service reminders, on-line diagnostics and statistics
- Maintenance warnings and soak testing facilities
- One-man maintenance
- Floating background and drift compensation
- Programmable day/night functionality
- Coincidence within and between zones
- Timed and manual zone control
- I/O programming with Boolean functions (maximum allocated input memory = 300)
- Scandinavian variants with Scandinavian firemans key available
- EN54 and CPD certified

FP1216C-18

1200 Series - Addressable Fire Panel with 2-4 Loops 16 Zone LED's - Polish

Spécifications techniques

Général

Taille du réseau (nœuds) supérieur à 128

Électrique

Consommation électrique 200 VA

Tension de fonctionnement 230 VAC (+10%, -15%), 47-63 Hz
21 to 28 VDC

Consommation de courant 200 mA @ 24 VDC (operation)
<240 mA @ 24 VDC (alarm)

Boucle

Capacité maximale de boucle de masse 4

Quantité de dispositifs en boucle <128 addresses (protocol dependent)

Cote de câble <2 km, Ø 1 mm, 300 nF/km, 100 ohm

Zone

Capacité maximale de zone jusqu'à 255

Batterie de secours

En charge Battery charger: 27.3 VDC at 20°C, 36 mV/°C

Batteries supportées dans le boîtier 2 x 12 V (7 to 45 Ah)

Caractéristiques physiques

Types de format Moyenne

Dimensions physiques 445 x 445 x 120 mm

Poids net 9 kg (no batteries)

Couleur Blanc (RAL 9016)

Type de montage Montage en surface

Environnement

Température de fonctionnement -5°C to +40°C

Température de stockage -20°C to +60°C

Indice de protection IP54

Régulateur

Certification EN54-2, EN54-4

Electrical

Auxiliary supply (24 VDC) 9 to 28 VDC @ 1 A (max)

Auxiliary supply (5 VDC) 5 VDC (±0.1V) 75 mA (max)

Loop

Loops per panel 4 (Class A), 8 (Class B)

Loop current <500 mA

Inputs / Outputs

Relays 4 (2A @ 24 VDC - 60W)

Supervised Relays 4 (24 VDC, 30 ohm, 120 nF, 500 m)

Inputs (Opto Isolated) 4 (15 VAC/0 to 28 VDC)

Inputs (Supervision selectable) 4

Zone indicators per panel 16 (fire & fault)