

9-30521

Minilaser Modulo espansione ingressi/uscite relè (opzionale)

Programmable Inputs

The Input/Output functional module extends the MiniLaser's interface capabilities by providing programmable ASD inputs that support key external control and supervision functions. These inputs can be configured for Remote Day/Night Mode changeover, Remote Reset, and ClassiFire Override, in addition to power-supply fault monitoring, enabling seamless integration with fire alarm control panels, building management systems, and site-specific control logic.

ClassiFire Override is a particularly valuable function, allowing the detector's normal sensitivity to be temporarily reduced by a pre-programmed percentage. This feature is designed to accommodate predictable and controlled environmental conditions that may otherwise lead to unwanted alarms, such as theatre stage effects, controlled smoke release, or open fires in heritage buildings. By dynamically adjusting sensitivity while maintaining full aspirating detection functionality, ClassiFire Override supports operational continuity without compromising overall system integrity.

Programmable Outputs

The Input/Output functional module extends the MiniLaser's interface capability by providing additional programmable outputs for enhanced external signalling and system integration. The Input/Output functional module adds five additional programmable outputs, complementing the detector's standard relay outputs and increasing flexibility for connection to fire alarm control panels, building management systems, and other external monitoring or control interfaces. The five outputs may be used to report the 4 alarm levels of the ASD, plus an additional fault output. Being able to report all 4 alarm levels is a requirement in certain applications where various actions or alarms are required based on the development of smoke and/or fire.

Configuration

All input and output functions can be configured using the Remote configuration software via the MiniLaser USB-C interface, allowing full access to advanced settings, diagnostics, and maintenance features. For rapid installation and commissioning, MiniLaser also supports an easy dip-switch configuration mode, enabling operation without a PC. When this installation mode is used, the inputs and outputs operate with preloaded default behaviors, ensuring predictable and standardized functionality straight out of the box while still allowing later refinement through software if required.



Dettagli

- I/O Expansion for MiniLaser : Designed specifically for use with MiniLaser Aspirating Smoke Detectors to extend system input and output capabilities
- Two Programmable Inputs : Provides two inputs that can be wired and configured via the Remote application to support external control or monitoring functions.
- Five Latched Relay Outputs : Includes five normally open or normally closed latched relay outputs for interfacing with external systems and devices.
- Integration via Expansion Sub-Module : Installs directly into the MiniLaser Expansion Sub-Module, supporting a modular system architecture.
- Flexible Slot Installation : Can be installed in either slot 1 or slot 2 within the expansion sub-module to support adaptable system layouts.
- Clear Device Status Indication : Features an onboard status LED that indicates power, communication status, and communication faults.

9-30521

Minilaser Modulo espansione ingressi/uscite relè (opzionale)

Specifiche tecniche

Ingresso

Quantità in entrata	2
Tipo di input e intervallo	Supervised
Termine	15 K Ω 5% 1/4 W
Programmabile	Yes

Uscita

Quantità in uscita	5
Tipo di uscita e intervallo	Voltage free (contact rating 2 A at 30 VDC / NO/NC/C)
Programmabile	Yes

Fisico

Dimensioni fisiche	92 x 67 x 19 mm (W x H x D)
--------------------	-----------------------------

Ambientale

Temperatura operativa	-10 to +60°C
Umidità relativa	0 to 90% noncondensing
Environment	Interno

Regolatorio

Certificazioni	CPR, EN54-20
----------------	--------------



In quanto azienda in continua innovazione, Kidde Global Solutions si riserva il diritto di modificare le specifiche del prodotto senza preavviso. Per avere informazioni sempre aggiornate, visita it.firesecurityproducts.com online o contatta il tuo riferimento commerciale.

Last updated on 3 September 2026 - 9:14