GS330

Relais Interface voor GS30x serie

Interface Unit

The GS330 is a high security interface unit that can be used when you want to connect the GS300/310 glass break detectors for balanced DC loops to a control panel without balanced loop connection. The GS330 can also be used if the balanced loop of the control panel has a loop voltage lower then 6 V or if you want to divide a large number of glass break detectors into smaller zones.

Features

The GS118N is equiped with a tamper proetected cast metal housing. The detector loop is double balanced and has separate LED indication for alarm and tamper alarm (open loop or short cuircuit). The interface unit can be remote reset with a "+" or "-" pulse from the control panel. The polarity is set with a jumper.





Details

- Plastic housing
- Balanced loop
- Relay output
- LED alarm indicatior
- Reset button
- LED tamper indication
- Remote reset feature
- VdS Stickers provided

GS330

Relais Interface voor GS30x serie

Technische specificaties

Algemeen

Accessoire groep	Glasbreuksensoren
Type	Reserveonderdeel

Elektrisch

Waarde voeding	10 to 15 VDC
Stroomverbruik	8 mA at 12 V (normal) 17 mA at 12 VDC (alarm)

Fysiek

Fysieke afmetingen	85 x 85 x 26 mm

Omgeving

Bedrijfstemperatuur	-30 to +60°C

Max. ripple

	2 V

Alarm output

	120 mA at 15 V

Tamper

	15 VDC, 120 mA

Als een bedrijf van innovatie behoudt Kidde Global Solutions zich het recht voor productspecificaties zonder kennisgeving te wijzigen. Ga voor de nieuwste productspecificaties online naar nl.firesecurityproducts.com of neem contact op met uw verkoopvertegenwoordiger.

Last updated on 18 June 2026 - 14:24