

Digital audio interface

EST-ISLE



1488-CPR-0718/W



Overview

The EST-ISLE is both a communication module enabling integration with external systems via RS485 protocol, and an audio signal splitter. Address settings – Number of addresses in the range of 0-F (16 addresses).

Local AUDIO IN – 4 input channels on the 8 pin connector. For easier and faster connection of audio sources, Phoenix-type connectors

can be used. LOCAL AUDIO IN jack (8 pin connector Phoenix) is bridged with LOCAL AUDIO OUT (RJ-45).

Output amplifiers – RJ-45 connector for the 4-channel amplifier.

Local AUDIO OUT – RJ-45 connector for input signals to the system.

PSM – RJ-45 connector for the link with power manager..

