



PS48VDC100W-DIN

100-240V AC Input 48VDC 100W Power Supply with DIN rail mount

Overview

Carrier Fire & Security's wide range of power supplies provide solutions for all the majority of various applications. Available in wall format with adaptors, Carrier Fire & Security supplies can be used with all major power plugs. Solutions include both in wall and "power brick" configurations. Switching supplies include advanced technology and power savings, meeting Level V (5) International Efficiency in compliance with California Energy Commission, Energy Star and the EU Code of Conduct for external power supplies. Supplies can be mixed and matched to a variety of Carrier Fire & Security products to meet installation requirements.



Einzelheiten

- CE approved
- UL approved
- CSA approved
- Compact power supplies for use with PoE Switches Media Converters
- Low voltage outputs
- Models for Europe and UK region
- In line power supply

PS48VDC100W-DIN

100-240V AC Input 48VDC 100W Power Supply with DIN rail mount

Technische Spezifikationen

Elektrische Angaben

Eingangsspannung	90 to 264 VAC, 47 to 63 Hz
------------------	----------------------------

Ausgang

Ausgangsleistung	48 VDC
------------------	--------

Ausgangsstrom	2 A
---------------	-----

Physikalisch

Abmessungen	55 x 90 x 100 mm
-------------	------------------

Nettogewicht	420 g
--------------	-------

Farbe	Weiß
-------	------

Formfaktor	DIN Schienen Montage
------------	----------------------

Regulativ

Kompatibilität	CE, REACH, RoHS 2, WEEE
----------------	-------------------------

Standards Conformance

EMC	CISPR 22 Class B
-----	------------------

EMC	EN55022 Class B
-----	-----------------

EMC	EN61204-3 Class B
-----	-------------------

EMC	FCC parts 15 Class B
-----	----------------------

BSMI : EMS requirements	EN55024
-------------------------	---------

BSMI : EMS requirements	IEC-61000-4-2
-------------------------	---------------

BSMI : EMS requirements	IEC-61000-4-3
-------------------------	---------------

BSMI : EMS requirements	IEC-61000-4-4
-------------------------	---------------

BSMI : EMS requirements	IEC-61000-4-5
-------------------------	---------------

BSMI : EMS requirements	IEC-61000-4-6
-------------------------	---------------

BSMI : EMS requirements	IEC-61000-4-8
-------------------------	---------------

BSMI : EMS requirements	IEC-61000-4-11
-------------------------	----------------



Als innovatives Unternehmen behält sich Kidde Global Solutions das Recht vor, Produktspezifikationen ohne Ankündigungen zu ändern. Für die aktuellsten Produktspezifikationen, besuchen Sie bitte de.firesecurityproducts.com online oder kontaktieren Sie bitte unsere Vertriebsmitarbeiter.