

## **UX-TOUCH01**

#### 7" Wi-Fi Touchscreen compatible with ZeroWire & xGen

#### Overview

The 7" TouchScreen provides a new way to interact with ZeroWire or xGen control panels. Accommodating up to four 7" TouchScreens per system, System owners can control their system from multiple locations throughout their property.

#### Communication

The 7" Touchscreen connects to ZeroWire or xGen control panels wirelessly via Wi-Fi® and features an icon-operated interface that's nearly identical to the UltraSync mobile app. The common interface between the 7" Touchscreen and the mobile app helps to reduce operator learning time and improve the overall user experience.

#### At a glance visibility

The 7" Touchscreen provides at-a-glance visibility to system status and easy operation through an icon-rich interface. It also provides audible signals to indicate when the system is in an arming/disarming sequence and will siren when the system is in alarm.



#### **Details**

- Up to four 7" TouchScreens supported on a single ZeroWire/ xGen panel
- Connectivity via a wireless Wi-Fi router
- Micro-USB power supply
- Tabletop or wall-mount placement
- Controls for individual as well as all areas/partitions of a ZeroWire/ xGen system: arming/disarming, automations, lighting control, door lock control, thermostat control, live video and recorded clips, systems settings and programming.

# UX-TOUCH01 7" Wi-Fi Touchscreen compatible with ZeroWire & xGen

### **Technical specifications**

General	
User interface	TFT LCD 7" colour touch screen
Product line	xGen, ZeroWire
System	
Personal voice guide	No
Intercom functionality	No
Communication	
Communication type	Wireless
Wireless protocol	Wi-Fi 2.4 GHz
Electrical	
Power supply type	100 to 240 VAC
Physical	
Physical dimensions	192 x 116 x 16 mm
Net weight	760 g
Colour	White
Form factor	Horizontal
Mounting type	Desk-based, Wall mount
Material	ABS
Environmental	
Vandal proof	No
Environment	Indoor
Regulatory	
Compliancy	CE



As a company of innovation, Carrier Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurity products.com online or contact your sales representative.