

TVK-610

TruVision RS485/IP keypad, 4-axis joystick, 12VDC

Overview

The TVK-600 keypad has been designed to be used with the line of TruVision NVRs, DVRs, PTZ cameras, encoders and decoders. A TVK-600 lets you easily control the monitor outputs of a recorder and a decoder, allows precise PTZ control, and gives you full control of every recorder's user interface using only the keypad.

Full featured

The TVK-600 contains all features to control a TruVision device efficiently.

The keypad can communicate via IP or RS485 with supported recorders and cameras.

The configuration of the keypad is done via a web browser.

Different user modes can be selected via the on-screen menu of the LCD display.

The keypad supports up to 1000 devices via keyboard mode.

Users can navigate through the menu of a recorder and control PTZ cameras via the 4-axis joystick.

Why TVK-600?

The TVK-600 lets you control your video system via one user interface without using a PC.

Applications

The TVK-600 is ideal for guard rooms and monitoring centers.



Dettagli

- Control a variety of NVRs, DVRs, decoders, PTZ cameras with one keypad
- Communication via IP or RS485
- 4-axis joystick
- Numeric and functional buttons
- Supports PTZ control (analog and IP)
- Control monitor outputs of recorders
- Supports up to 1000 devices via keyboard mode
- Configuration and device management via webpage
- Control the recorder OSD
- Set and call presets and preset tours of PTZ cameras

TVK-610

TruVision RS485/IP keypad, 4-axis joystick, 12VDC

Specifiche tecniche

Generale

Tastiera/tipo di controller Analogico / Seriale, IP

Controllo

Tipo di joystick 4-assi

Pulsanti Numeric and functional

Interfaccia utente

Tipo display 128 x 64 pixel screen

Interfaccia

Interfaccia di connessione Ethernet, RS-485

Elettrico

Tipo di alimentatore 12 VDC

Valore di alimentazione 12 V

Consumo di energia <= 4.5 W

Fisico

Dimensioni fisiche 435 x 193 x 110 mm

Peso netto 1 kg

Colore Nero

Ambientale

Temperatura operativa -10 to +55°C

Umidità relativa 10 to 90%

Regolatorio

Conformità CE, RoHS, WEEE

Interfaces

Network interface 10 / 100 Mbps self-adaptive Ethernet interface

USB USB 2.0

Supported products

Devices

TruVision PTZ cameras:

TruVision S1 PTZ cameras (TVP-310x / 110x / 3122 / 1122)

TruVision IP Compact PTZ cameras

TruVision IP Full Size PTZ cameras

TruVision Stainless Steel IP PTZ cameras

TruVision TVI PTZ cameras

TruVision recorders:

TVN 11 series

TVN 21 series

TVN 22 series

TVR 15HD series

TVR 45HD series

TVR 46 series

TVR 40 series

TVR 41 series

TVR 42 series

TVR 60 series

TruVision decoders:

TVE-DEC11

TVE-DEC12

TruVision encoders and non-PTZ IP cameras:
only as input.

See configuration manual (Appendix A) for more
detailed information.



In quanto azienda in continua innovazione, Carrier Fire & Security si riserva il diritto di modificare le specifiche del prodotto senza preavviso. Per avere informazioni sempre aggiornate, visita it.firesecurityproducts.com online o contatta il tuo riferimento commerciale.

Last updated on 15 October 2024 - 14:39